# **DATA HUB**

v 1.2 | 14 June 2021

### 485 Bus Distribution

#### **Features**

- Adds 5 device ports to the SDN bus line
- Wiring stub length up to 200 ft.
- Powered by the SDN bus line
- Includes bus segment status LEDs for:
  - Power
  - Communication
  - End of line notification
- Protects system components from miswire
- Uses RJ45 connectors

### Input

SDN Bus Power

### **Power Consumption**

1 SDN Power Unit, 10 mA

## **Material (Indoor Use Only)**

ABS (94 - V0 Fireproof)

### **Operating Temperature Range**


Ambient Temperature

### **Shipping Weight**

1lb

# 4.88" -Somfy Data Hub MAGENUS 0.19"-2.44"





### Data Hub Specifications

For illustration purposes only

#### **Dimensions**

4.88" L x 2.24" W x 0.90" H (124mm x 57 mm x 23 mm)

#### Parts in the Box


#1870262


Data Hub

### Works with

- Janus
- 485 Decoflex
- RTS SDN Gateway
- Si.Fi

#### **Connections and Indicators**





	Element	Function
1.	Device Port	5 devices less than 200 ft. from the main bus lin e (each port has 200 ft. wire length limitation)
2.	SDN Bus Input	Input for bus signal s
3.	SDN Bus Output	Output for bus signal s